





BH65TWS User's Manual

Powering BH65TWS On / Off

Press and Hold the POWER button for 4 seconds to power ON. You will hear an audible tone. The blue LED will flash quickly to indicate that it is powered on and searching for a Bluetooth source to pair with.

To power the speaker off, press and hold the POWER button for 4 seconds.

NOTE: An additional battery icon may appear next to the Bluetooth icon at the top right of your phone/tablet's screen, indicating the speaker's battery level. This is compatible only with certain devices.

Connecting BH65TWS via Bluetooth

Once powered on, the speaker will automatically enter pairing mode. Go into your phone/tablet's Bluetooth settings and enable Bluetooth. Next, enter the Bluetooth device list and select Bell+Howell BH65TWS. After selected, wait a

few seconds for the pairing to complete. Once the pairing is successful, you will hear an audible tone from the speaker and the LED will light up solid blue.

NOTE: The BH65TWS will automatically connect to a previously paired device if the paired device's Bluetooth radio is powered, enabled and within reachable distance.

Connecting BH65TWS via Auxiliary Input

If you would like to use a device that is not equipped with Bluetooth technology, simply connect the included auxiliary 3.5mm cable from your device to the Aux-In input at the side of the BH65TWS. The speaker will automatically enter auxiliary mode. While connected via Auxiliary, the only controls that will function on the speaker is the PLAY button and volume control. All other functions are controlled from the connected device.

Linking another BH65TWS for True Wireless Sound

The BH65TWS includes True Wireless Stereo (TWS) technology. This enables you to link two speakers to emit a true left / right stereo sound.

To connect two speakers over TWS make sure both speakers are powered on and only one of the speakers is connected to a Bluetooth device. The speaker connected to the Bluetooth device will be the master speaker. Press and hold the PLUS and MINUS buttons at the same time for two seconds. The LED light on the speaker will flash blue quickly, indicating it is searching for another speaker to connect to. The master speaker will automatically connect with the auxiliary speaker. Once the two speakers are connected LED indicator on both speakers will say lit blue.

To forget the last TWS pairing press and hold the PLUS and MINUS buttons at the same time for two seconds on either one of the speakers. this will forget the last TWS and Bluetooth connection.

Controlling the Sound on Your BH65TWS

PLAY / PAUSE

Tap the PLAY button.

VOLUME UP / DOWN

Tap the MINUS button to decrease the volume.

Tap the PLUS button to increase the volume.

FORWARD / BACKWARD TRACK

Press and hold the PLUS button to skip a track forward. Press and hold the MINUS button to go to the previous track.

ANSWER / END PHONE CALL

Tap the PLAY/PAUSE button.

DECLINE PHONE CALL

Press and hold the PLAY/PAUSE button.

Answering or Making Calls

If there is an incoming call on your paired phone/tablet, the music will pause and the ring tone will play from the BH65TWS speaker. To answer a call, simply press the PLAY/PAUSE button.

To end a call, simply press the PLAY/PAUSE button. Press and hold the PLAY/PAUSE button to decline a phone call.

NOTE: For best performance and clarity, operate the BH65TWS within an arm's length. Ensure that the microphone faces your direction.

Charging your BH65TWS

Plug the small end of the included micro USB cable into the micro USB port on the back of the speaker. Plug the other end of the cable into a 5V AC adaptor (not included). Once plugged in, the charging LED on the side of the speaker will

light up red. It will turn off once the internal battery is fully charged.

NOTE: The BH65TWS can only be charged with 5V adapters/USB ports. Quick charging devices over 5V may cause damage.

Factory Reset

If you are experiencing connectivity issues, you may need to perform a hard reset on your BH65TWS. To do so, push the reset button on the side of the speaker, you can also press and hold the PLAY/PAUSE and the PLUS buttons at the same time for 3 seconds.

Specifications

Bluetooth Version: 5.0 Built-in Lithium-Ion Battery: 3.7V, 2200mAh Charging Voltage: 5V

Speaker: 52mm, 4Ω 3W x 2 Frequency: 80Hz-18KHz Distortion: ≤0.5% Effective Distance: 10M Elite Brands Inc., 40 Wall Street, 61st Floor New York, NY 10005 · Tel: 1-800-441-1100 www.elitebrands.com

Distributed under license of BHH LLC by ELITE BRANDS INC ©2021 www.bellhowellcameras.com

The Bluetooth word mark and logos are registered trademarks owned by the Bluetooth SIG, and any use of such marks by Elite Brands Inc. is under license. Other trademarks and trade names are those of their respective owners.